

# **ICS-40619 Product Brief**

# High SNR Microphone with Differential Output and Low-Power Mode

#### **GENERAL DESCRIPTION**

The ICS-40619 is an analog MEMS microphone with very high SNR and a low-power AlwaysOn mode. The ICS-40619 includes a MEMS microphone element, an impedance converter, and a differential output amplifier.

This microphone features a low-power mode, which is activated when the supply voltage is <2.0 V. In this mode, the ICS-40619 operates with 55  $\mu$ A.

Other high-performance specifications include 132 dB SPL acoustic overload point in high performance mode, tight ±1 dB sensitivity tolerance and enhanced immunity to both radiated and conducted RF interference.

The ICS-40619's electro-acoustic performance matches the bottom port ICS-40618, making this pair of microphones suitable to use together in applications requiring both top and bottom port devices.

The ICS-40619 is available in a small 3.50 mm  $\times$  2.65 mm  $\times$  0.98 mm top port surface-mount package.

#### **APPLICATIONS**


- Smartphones
- "AlwaysOn" listening
- Wearable devices
- Still and video cameras
- Bluetooth headsets
- Security and surveillance

#### **FEATURES**

SPEC	HIGH PERFORMANCE	LOW-POWER
	MODE	MODE
SNR	67 dBA	67 dBA
Current	165 μΑ	55 μΑ
AOP	132 dB SPL	129 dB SPL

- Differential non-inverting analog output
- –38 dBV sensitivity (differential)
- ±1 dB sensitivity tolerance
- Extended frequency response from 50 Hz to 20 kHz
- Enhanced RF immunity
- -85 dB PSRR
- 3.50 × 2.65 × 0.98 mm top port surface-mount package
- Compatible with Sn/Pb and Pb-free solder processes
- RoHS/WEEE compliant

### **FUNCTIONAL BLOCK DIAGRAM**



## **ORDERING INFORMATION**

PART	TEMP RANGE	PACKAGING
ICS-40619	-40°C to +85°C	13" Tape and Reel
EV_ICS-40619-FX	_	

Document Number: PB-000023 Revision: 1.0 Rev. Date: 02/18/2016