# TW2010/TW2012 Magnet Mount GPS L1 Antenna

The TW2010/TW2012 by Tallysman Wireless is a professional grade, magnet mount, GPS L1 antenna, specially designed for industrial, agricultural and military precision positioning and timing applications.

The TW2010/TW2012 features a high performance custom tuned ceramic patch element, 15 KV ESD circuit protection, a high gain two-stage low noise amplifier (LNA) with a mid section high rejection SAW filter. The TW2012 also has a tight SAW pre-filter to provide unparalleled out-of-band signal rejection. It covers the GPS L1 and SBAS (WAAS/EGNOS/MSAS) frequency band (1572.5 to 1578 MHz), and it offers great circular polarized signal reception, multipath rejection and out of band signal rejection.

The TW2010 is housed in a compact, industrialgrade weather-proof, magnet mount enclosure.

#### **Applications**

Tallysman

- High Accuracy & Mission Critical GPS •
- Precision Agriculture, Mining & Construction
- Military & Security
- Avionics •
- Law Enforcement & Public Safety
- Fleet Management & Asset Tracking

#### Features

- Very low noise LNA: 1 dB •
- Great axial ratio: <1dB at Zenith •
- High rejection SAW filter •
- High gain: 28 dB typ. •
- Low current: 10 mA typ. •
- ESD circuit protection: 15 KV
- Wide voltage input range: +2.5 to 16 VDC
- Weather proof housing: IP67

### **Benefits**

- Great multipath rejection •
- Increase system accuracy ٠
- Excellent signal to noise ratio •
- Great out of band signal rejection •
- Ideal for harsh environments
- **RoHS** compliant

Dimensions (mm)

Dimensions (mm)



# TW2010/TW2012 Magnet Mount GPS L1 Antenna

**Specifications** Vcc = 3V, over full bandwidth, T=25°C

### Antenna

Tallysman

Architecture Antenna Gain (100mm ground plane) Axial Ratio (over full bandwidth)

### **Electrical**

Architecture Frequency Bandwidth Polarization Gain

**Out-of-Band Rejection** 

<1560 MHz >1600 MHz >1620 MHz

VSWR (at LNA output) Noise Figure Supply Voltage Range Supply Current ESD Circuit protection

## **Mechanicals & Environmental**

Mechanical Size Cable Operating Temp. Range Enclosure Weight Attachment Method Environmental Shock Vibration Warranty Custom single-feed ceramic patch 4 dBic at 90° 1dB at 90°, 6dB at 20°

Input LNA, mid section SAW filter, output LNA 1572.5 to 1578 MHz RHCP 28 dB min (TW2010) 25dB (TW2012). TW2010 TW2012 >42 dB >50 dB >31 dB >55 dB >70dB >45 dB <1.5:1 typ. 1.8:1 max. 1 dB typ. (TW2010) 3 dB (TW2012) +2.5 to 16 VDC nominal (12 VDC recommended max.) 10 mA typ at 25°C. 15 KV air discharge

57 mm dia. x 15 mm H RG174 -40 to +85 °C Radome: ASA Plastic, Base: Zamak white metal 150 g Magnet or permanent (pre-tapped 4 x 6-32UNC) IP67 and RoHS compliant Vertical axis: 50 G, other axes: 30 G 3 axis, sweep = 15 min, 10 to 200 Hz sweep: 3 G One year – parts and labour

## **Ordering Information**

Part Numbers:

TW2010 - GPS L1 antenna33-2010-xx-yyyyTW2012 - GPS L1 antenna w/pre-filter33-2012-xx-yyyy

Where xx = connector type and yyyy = cable length in mm

Please refer to the Ordering Guide (<u>http://www.tallysman.com/orderingguide.php</u>) for the current and complete list of available connectors.

### **Tallysman Wireless Inc**

36 Steacie Drive Ottawa ON K2K 2A9 Canada Tel 613 591 3131

Fax 613 591 3121

sales@tallysman.com

The information provided herein is intended as a guide only and is subject to change without notice. This document is not to be regarded as a guarantee of performance. Tallysman Wireless Inc. hereby disclaims any or all warranties and liabilities of any kind. © 2010 Tallysman Wireless Inc. All rights reserved. Rev 5.3